



Light Sensitivity	Color: < 2 lux, B/W: < 0.2 lux, (50 IRE, 100% scene reflection)
Connection TP	4-pole RJ11E (Video, Audio, Power, Comm.)
Input Voltage	24 VDC
Power Consumption	< 2 W
AGC Range	Automatic
Electronic Shutter Range	1/50 sec. to 1/100,000 sec.
Backlight Compensation	Weighting window in center of picture Window size between 33-40% of picture height
Audio Output	Built-in electret microphone 300 Hz–4 kHz
White Balance	Automatic 2500-9000K (only for color cameras)

#### Lens Type

PAL		NTSC	
VCM7C130/00T	VC7C1305T	3 mm fixed focal lens, f 2.0	
VCM7C230/00T	VC7C2305T	3-6 mm varifocal lens, f 1.2	
VCM7C272/00T	VC7C2725T	2.8-10 mm CS-mount varifocal DC-iris lens, f 1.4-360	
VCM7C275/00T	VC7C2755T	5-50 mm CS-mount varifocal DC-iris lens, f 1.7-360	
VCM7D130/00T	VC7D1305T	3 mm fixed focus lens, f 2.0	
CCIR		EIA	
VCM7B272/00T	VC7B2725T	2.8-10 mm CS-mount varifocal DC-iris lens, f 1.4-350	

#### Weight

PAL		NTSC	
VCM7C130/00T	VC7C1305T	approx. 0.25 kg (0.55 lbs.)	
VCM7C230/00T	VC7C2305T	approx. 0.25 kg (0.55 lbs.)	
VCM7C272/00T	VC7C2725T	approx. 0.25 kg (0.55 lbs.)	
VCM7C275/00T	VC7C2755T	approx. 0.34 kg (0.75 lbs.)	
VCM7D130/00T	VC7D1305T	approx. 0.31 kg (0.68 lbs.)	
CCIR		EIA	
VCM7B272/00T	VC7B2725T	approx. 0.25 kg (0.55 lbs.)	

#### Dimensions (HxWxD)

PAL		NTSC	
VCM7C130/00T	VC7C1305T	74x70x65 mm (2.9x2.8x2.6 in)	
VCM7C230/00T	VC7C2305T	74x70x85 mm (2.9x2.8x3.3 in)	
VCM7C272/00T	VC7C2725T	74x70x105 mm (2.9x2.8x3.7 in)	
VCM7C275/00T	VC7C2755T	74x70x115 mm (2.9x2.8x4.5 in)	
VCM7D130/00T	VC7D1305T	Ø 115x80 (H) (4.5x3.1 in)	
CCIR		EIA	
VCM7B272/00T	VC7B2725T	74x70x105 mm (2.9x2.8x3.7 in)	
Operational Temperature	-10°C ... 45°C (14°F ... 113°F)		

CCIR	EIA
Storage Temperature	-25°C ... 70°C (-13°F ... 158°F)
Relative Humidity	0% to 95% RH (Non-condensing)
Add-ons	Cable 15 m (45 ft.) (4-wire dual twisted pair) Mono-pod

#### Ordering Information

<b>VCM7C130/00T, Eazeo Digital Color Camera</b> 1/4-inch with 3 mm integrated lens, PAL	<b>VCM7C130/00T</b>
<b>VCM7D130/00T, Eazeo Digital Color Camera</b> 1/4-inch minidome camera with 3 mm integrated lens, PAL	<b>VCM7D130/00T</b>
<b>VCM7C230/00T, Eazeo Digital Color Camera</b> 1/4-inch with 3-6 mm varifocal integrated lens, PAL	<b>VCM7C230/00T</b>
<b>VCM7C272/00T, Eazeo Digital Color Camera</b> 1/4-inch with 2.8-10 mm varifocal, DC-iris, CS-mount lens, PAL	<b>VCM7C272/00T</b>
<b>VCM7C275/00T, Eazeo Digital Color Camera</b> 1/4-inch with 5-50 mm varifocal, DC-iris, CS-mount lens, PAL	<b>VCM7C275/00T</b>
<b>VCM7H272/00T, Eazeo Digital Color Camera</b> 1/4-inch outdoor camera assembly, includes VCM7C272/00T camera and VCM1353/00T housing, PAL	<b>VCM7H272/00T</b>
<b>VCM9736/10T, Eazeo Digital Color Camera</b> Covert color camera in PIR housing, PAL	<b>VCM9736/10T</b>
<b>VCM9736/11T, Eazeo Digital Color Camera</b> Covert color camera in smoke detector housing, PAL	<b>VCM9736/11T</b>
<b>VCM7B272/00T, Eazeo Digital B/W Camera</b> 1/4-inch with 2.8 - 10 mm varifocal, DC-iris CS-mount lens, CCIR (for use with color observation system)	<b>VCM7B272/00T</b>
<b>VC7C1305T, Eazeo Digital Color Camera</b> 1/4-inch with integrated 3 mm fixed lens, NTSC	<b>VC7C1305T</b>
<b>VC7D1305T, Eazeo Digital Color Camera</b> 1/4-inch, minidome with integrated 3 mm fixed lens, NTSC	<b>VC7D1305T</b>
<b>VC7C2305T, Eazeo Digital Color Camera</b> 1/4-inch with 3-6 mm varifocal integrated lens, NTSC	<b>VC7C2305T</b>
<b>VC7C2725T, Eazeo Digital Color Camera</b> 1/4-inch with 2.8-10 mm varifocal, DC-iris CS-mount lens, NTSC	<b>VC7C2725T</b>

## Ordering Information

<b>VC7C2755T, Eazeo Digital Color Camera</b> 1/4-inch with 5-50 mm varifocal, DC-iris CS-mount lens, NTSC	<b>VC7C2755T</b>
<b>VC7H2725T, Eazeo Digital Color Camera</b> 1/4-inch outdoor camera assembly, includes VC7C2725T camera and VCM1353/00T housing, NTSC	<b>VCM7H2725T</b>
<b>VC973650T, Eazeo Digital Color Camera</b> Covert color camera in PIR housing, NTSC	<b>VC973650T</b>
<b>VC973651T, Eazeo Digital Color Camera</b> Covert color camera in smoke detector housing, NTSC	<b>VC973651T</b>
<b>VC7B2725T, Eazeo Digital B/W Camera</b> 1/4-inch with 2.8 - 10 mm varifocal, DC-iris CS-mount lens, EIA (for use with color observation system)	<b>VC7B2725T</b>
<b>Accessories</b>	
<b>VSS7390/11T Color Switcher System</b> 14-inch monitor, PAL, 4 input switcher with one camera VCM7C130/00T, 240 VAC, 50 Hz	<b>VSS7390/11T</b>
<b>VSS7390/21T Color Switcher System</b> 14-inch monitor, PAL, 4 input switcher with one camera VCM7C230/00T, 240 VAC, 50 Hz	<b>VSS7390/21T</b>
<b>VSS7390/31T Color Switcher System</b> 14-inch monitor, PAL, 4 input switcher with one camera VCM7C272/00T, 240 VAC, 50 Hz	<b>VSS7390/31T</b>
<b>VSS7390/41T Color Switcher System</b> 14-inch monitor, PAL, 4 input switcher with one minidome camera VCM7D130/00T, 240 VAC, 50 Hz	<b>VSS7390/41T</b>
<b>VSS8394/10T Color Multiplexer System</b> 14-inch monitor, PAL, 8 input Multiplexer, 240 VAC, 50 Hz. (without camera)	<b>VSS8394/10T</b>
<b>VSS8394/14T Color Multiplexer System</b> 14-inch monitor, PAL, 8 input multiplexer with four cameras VCM7C130/00T, 240 VAC, 50 Hz.	<b>VSS8394/14T</b>
<b>VSS8394/34T Color Multiplexer System</b> 14-inch monitor, PAL, 8 input multiplexer with four cameras VCM7C272/00T, 240 VAC, 50 Hz.	<b>VSS8394/34T</b>
<b>VSS8394/44T Color Multiplexer System</b> 14-inch monitor, PAL, 8 input multiplexer with four minidome cameras VCM7D130/00T, 240 VAC, 50 Hz.	<b>VSS8394/44T</b>
<b>VSS8394/74D Color Multiplexer System</b> 14-inch monitor, PAL, 8 input multiplexer with four cameras VCM7C130/00T, 240 VAC, 50 Hz. + Eazeo DVR1B1161	<b>VSS8394/74D</b>
<b>VSS8394/94T Color Multiplexer System</b> 14-inch monitor, PAL, 8 input multiplexer with four cameras VCM7C130/00T, 240 VAC, 50 Hz + VCR RT30A/51	<b>VSS8394/94T</b>

## Ordering Information

<b>VSS7902/00T Alarm / Action Box</b> For detectors and door locks, PAL	<b>VSS7902/00T</b>
<b>VSS7915/00T Outdoor Video Intercom unit</b> Signal TP cable, 4-pole RJ11E, 24 VDC, PAL	<b>VSS7915/00T</b>
<b>VSS9490/90T Color Monitor</b> 14-inch add-on monitor for color observation systems, PAL	<b>VSS9490/90T</b>
<b>VSS7390/11U Color Switcher System (UK)</b> 14-inch monitor, PAL, 4 input switcher with one camera VCM7C130/00T, 240 VAC, 50 Hz	<b>VSS7390/11U</b>
<b>VSS7390/21U Color Switcher System (UK)</b> 14-inch monitor, PAL, 4 input switcher with one camera VCM7C230/00T, 240 VAC, 50 Hz	<b>VSS7390/21U</b>
<b>VSS7390/31U Color Switcher System (UK)</b> 14-inch monitor, PAL, 4 input switcher with one camera VCM7C272/00T, 240 VAC, 50 Hz	<b>VSS7390/31U</b>
<b>VSS7390/41U Color Switcher System (UK)</b> 14-inch monitor, PAL, 4 input switcher with one minidome camera VCM7D130/00T, 240 VAC, 50 Hz	<b>VSS7390/41U</b>
<b>VSS8394/10U Color Multiplexer System (UK)</b> 14-inch monitor, PAL, 8 input Multiplexer, 240 VAC, 50 Hz. (without camera)	<b>VSS8394/10U</b>
<b>VSS8394/14U Color Multiplexer System (UK)</b> 14-inch monitor, PAL, 8 input multiplexer with four cameras VCM7C130/00T, 240 VAC, 50 Hz.	<b>VSS8394/14U</b>
<b>VSS8394/34U Color Multiplexer System (UK)</b> 14-inch monitor, PAL, 8 input multiplexer with four cameras VCM7C272/00T, 240 VAC, 50 Hz	<b>VSS8394/34U</b>
<b>VSS8394/44U Color Multiplexer System (UK)</b> 14-inch monitor, PAL, 8 input multiplexer with four minidome cameras VCM7D130/00T, 240 VAC, 50 Hz	<b>VSS8394/44U</b>
<b>VSS8394/74U Color Multiplexer System (UK)</b> 14-inch monitor, PAL, 8 input multiplexer with four cameras VCM7C130/00T, 240 VAC, 50 Hz. + Eazeo DVR1B1161	<b>VSS8394/74U</b>
<b>VSS8394/94U Color Multiplexer System (UK)</b> 14-inch monitor, PAL, 8 input multiplexer with four cameras VCM7C130/00T, 240 VAC, 50 Hz + VCR RT30A/51	<b>VSS8394/94U</b>
<b>VS7390/11T Color Switcher System</b> 14-inch monitor, NTSC, 4 input switcher with one camera VC7C1305T, 120 VAC, 60 Hz	<b>VS7390/11T</b>
<b>VS7390/21T Color Switcher System</b> 14-inch monitor, NTSC, 4 input switcher with one camera VC7C2305T, 120 VAC, 60 Hz	<b>VS7390/21T</b>

## Ordering Information

**VS7390/31T Color Switcher System VS7390/31T**

14-inch monitor, NTSC, 4 input switcher with one camera VC7C2725T, 120 VAC, 60 Hz

**VS7390/41T Color Switcher System VS7390/41T**

14-inch monitor, NTSC, 4 input switcher with one minidome camera VC7D1305T, 120 VAC, 60 Hz

**VS8394/11T Color Multiplexer System VS8394/11T**

14-inch monitor, NTSC, 8 input multiplexer with one camera VC7C1305T, 120 VAC, 60 Hz

**VS8394/21T Color Multiplexer System VS8394/21T**

14-inch monitor, NTSC, 8 input multiplexer with one camera VC7C2305T, 120 VAC, 60 Hz

**VS8394/31T Color Multiplexer System VS8394/31T**

14-inch monitor, NTSC, 8 input multiplexer with one camera VC7C2725T, 120 VAC, 60 Hz

**VS8394/41T Color Multiplexer System VS8394/41T**

14-inch monitor, NTSC, 8 input multiplexer with one camera VC7D1305T, 120 VAC, 60 Hz

**VS8394/14T Color Multiplexer System VS8394/14T**

14-inch monitor, NTSC, 8 input multiplexer with four cameras VC7C1305T, 120 VAC, 60 Hz

**VS8394/34T Color Multiplexer System VS8394/34T**

14-inch monitor, NTSC, 8 input multiplexer with four cameras VC7C2725T, 120 VAC, 60 Hz

**VS8394/44T Color Multiplexer System VS8394/44T**

14-inch monitor, NTSC, 8 input multiplexer with four cameras VC7D1305T, 120 VAC, 60 Hz

**VS8394/74D Color Multiplexer System VS8394/74D**

14-inch monitor, NTSC, 8 input multiplexer with four cameras VC7C1305T, 120 VAC, 60 Hz + Eazeo DVR1B1161

**VS8394/94T Color Multiplexer System VS8394/94T**

14-inch monitor, NTSC, 8 input multiplexer with four cameras VC7C1305T, 120 VAC, 60 Hz + VCR RT30A/61

**VS79025T Alarm/Action Box VS79025T**

For detectors and door locks, NTSC

**VS79155T Outdoor Video Intercom unit VS79155T**

Signal TP cable, 4-pole RJ11E, 24 VDC, NTSC

**VS9409/91T Color Monitor VS9409/91T**

14-inch add-on monitor for color observation systems, NTSC

**RC283511/01 IR Remote Control RC283511/01**

For color observation systems, PAL/NTSC

**VCM1152/10T Indoor Housing VCM1152/10T**

Protective cover, for observation system cameras, PAL/NTSC & CCIR/EIA

## Ordering Information

**VCM1353/00T Outdoor Housing VCM1353/00T**

For observation system cameras, heater, powered by monitor, PAL/NTSC & CCIR/EIA

**Europe, Middle East, Africa:**  
Bosch Security Systems B.V.  
P.O. Box 80002  
5600 JB Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Americas:**  
Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Asia-Pacific:**  
Bosch Security Systems Pte Ltd  
38C Jalan Pemimpin  
Singapore 577180  
Phone: +65 6319 3450  
Fax: +65 6319 3499  
apr.securitysystems@bosch.com  
www.boschsecurity.com

**Represented by**